

Shapes by Bailey lights



				Chianti 4W	Bourbon 4W	Pinot 4W	Art-Deco 4W	Magnum 4W	
				Gold	141870	141871	141873	141875	141877
				Black	143109	141872	141874	141876	
Brand	Model	Load (LED)	Type	Dimming compatibility					
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1 2-5	1 2-5	1 2-5	1 2-5	1 2-5	
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-5	1-5	
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-5	1-5	
Gira	238500	3-100W	R,L,C - Touch	1 2-5	1 2-5	1 2-5	1 2-5	1 2-5	
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1-5	
Honeywell Peha	00260623	6-60W	R,L - Turn	1 2-5	1 2-5	1 2-5	1 2-5	1 2-5	
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1 2-5	1 2-5	1 2-5	1 2-5	1 2-5	
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	
Jung	225NVDE	3-100W	R,L - Turn	1-5	1-5	1-5	1-5	1-5	
Klemko	891042	1-200W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-5	1-5	1-5	1-5	
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	
Tradim	2490HP	5-70W	R,C - Turn	1 2-5	1 2-5	1 2-5	1 2-5	1 2-5	
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1 2-5	1 2-5	1 2-5	1 2-5	1 2-5	
Tradim	63103X-1	1x27W	Floor	1-5	1-5	1-5	1-5	1-5	
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	

* Recommended dimmer



				Teapot Earl 4W	Teapot Chai 4W	Aceto 4W	
				Clear	142440	142443	143040
				Gold	142441	142444	143041
				Milky	142442	142445	
				Black	142442	142445	143042

Brand	Model	Load (LED)	Type	Dimming compatibility		
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-2 3-5	1-2 3-5	1-2 3-5
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-5	1-5
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-5	1-5
Gira	238500	3-100W	R,L,C - Touch	1 2-5	1 2-5	1-5
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1 2-5	1 2-5	1-5
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1 2-5	1 2-5	1-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5
Klemko	891042	1-200W	R,C - Turn	1 2-5	1 2-5	1 2-5
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-5	1-5
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5
Tradim	2490HP	5-70W	R,C - Turn	1 2-5	1 2-5	1 2-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5	1-5
Tradim	63103X-1	1x27W	Floor	1-5	1-5	1-5
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5

* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels (≤ 20%)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior. * only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

Big Family



Papi 3W	Mami 3W	Johnny 3W	Benny 3W	Baby 3W	Jenny 4W	Billy 6W
80100038766	80100039415	80100039416	80100040746	80100040744	80100040745	80100041302

Brand	Model	Load (LED)	Type	Dimming compatibility									
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7	1-7			
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn							1-3			
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-5	1-2	3-5	1-2	3-5	1-2	3-5	1	2-5	
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-7	1-7	1-7	1-7	1-5	1-5	1-5	1-5		
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-7	1-7	1-7	1-7	1-5	1-5	1-5	1-5		
Gira	226200**	3-100W	R,L - Turn										
Gira	238500	3-100W	R,L,C - Touch	1-2	1-2	1-2	1-2	1	2-5	1-5	1	2-5	
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1	2-5	1-5	1-5		
Honeywell Peha	00260623	6-60W	R,L - Turn	1	2-5	1	2-5	1	2-5	1	2-5	1	2-5
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-5	1	2-5	1	2-5	1	2-5	1	2-5	
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5		
Jung	225NVDE	3-100W	R,L - Turn										
Klemko	891042	1-200W	R,C - Turn	1	2-5	1	2-5	1	2-5	1	2-5		
KlikAanKlikUit	ACC-250-LD	3-50W	Socket - Wireless		1	1	1						
KlikAanKlikUit	AWMD-250	3-24W	Module - Wireless										
KlikAanKlikUit	ACM-250-LD	3-50W	Wireless		1	1	1						
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-7	1-7	1-7	1-7	1-5	1-5	1-5	1-5		
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5		
Tradim	2490HP	5-70W	R,C - Turn	1-7	1-7	1-7	1-7	1	2-5	1	2-5	1	2-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5	1-5	1-5						
Tradim	63103X-1	1x27W	Floor	1-7	1-7	1-7	1-7	1-5	1-5	1-5	1-5		
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5		
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5		

* Recommended dimmer



Joey 3W	Papi 5W	Amy 3W	Ruby 3W	Drop 5W	Leo 8.5W
Gold: 142080		142083	142084	142210	143044
Black: 142081	142082				







Brand	Model	Load (LED)	Type	Dimming compatibility						
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7	
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1	2-5	1	2-5	1-2	3-5	1-5
Eltako	FUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-5	1-5	1-5	
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-5	1-5	1-5	
Gira	238500	3-100W	R,L,C - Touch	1	2-5	1-5	1-5	1	2-5	1-5
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1-5	1-5	
Honeywell Peha	00260623	6-60W	R,L - Turn	1	2-5	1	2-5	1	2-5	1-5
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1	2-5	1	2-5	1-5	1-5	
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	
Klemko	891042	1-200W	R,C - Turn	1-5	1-5	1-5	1-5		1-5	
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-5	1-5	1-5	1-5	1-5	
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	
Tradim	2490HP	5-70W	R,C - Turn	1-5	1	2-5	1-5	1	2-5	1-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)					1-5	1-5	
Tradim	63103X-1	1x27W	Floor	1-5	1-5	1-5	1-5	1-5	1-5	
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	1-5	
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	1-5	

* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels (≤ 20%)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior, only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low light levels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

Designs by Bailey lights

				Gatsby 4W	Fish 4W	Prop 4W	Duo 4W	Paint 7W	Bird 4W
									
				142764	143043	143095	143092 143093 143094	143045 143046	143625 143629
Brand	Model	Load (LED)	Type	Dimming compatibility					
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-5	1-5		1-5		1-5
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-5	1-5	1-5
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-5	1-5	1-5
Gira	238500	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-5	1	2-5
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1-5	1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1-5	1-5	1-5	1-5	1	2-5
Jung	1224LEUDE	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-5	1	2-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5
Klemko	891042	1-200W	R,C - Turn	1-5			1-5		1-5
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-7	1-5	1-5	1-5	1-5
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5
Tradim	2490HP	5-70W	R,C - Turn	1-5	1-5	1-5	1-5	1	2-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)		1-5	1-5	1-5		1-5
Tradim	63103X-1	1x27W	Floor	1-2	1-2	1-2	1-2	1-2	1-2
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	1-5

* Recommended dimmer

Spiraled Plus | BottLed | Silhouette



Plus 12W	Plus 15W	BottLed Slim	Silhouette 8W	Silhouette 12W
				
80100040763	80100040802	80100040758 80100040759 80100040760 80100040761 80100040762	80100040300 80100040301	80100040303 80100040304 80100040704 80100040705

Brand	Model	Load (LED)	Type	Dimming compatibility				
Bailey *	WW15031	3-70W	R,C - Turn	1-5	1-4	1-7	1-7	1-7
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn	1-3	1-3	1-3	1-3	
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-3	1-3	1-5	1-3	1-3
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-3	1-3
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-3	1-3
Gira	226200**	3-100W	R,L - Turn					
Gira	238500	3-100W	R,L,C - Touch		1-3			
Gira	245500	3-200W	Uni. Led - Turn	1-3	1-3	1-5	1-3	1-3
Honeywell Peha	00260623	6-60W	R,L - Turn		1-3		1-3	
Jung	1224LEUDE	3-100W	R,L,C - Touch	1-3	1-3	1-5	1-3	1-3
Jung	1730DD	3-60W	R,L,C - Turn	1-3	1-3	1-5	1-3	1-3
Klemko	891042	1-200W	R,C - Turn	1-3	1-3	1-5	1-3	1-3
KlikAanKlikUit	ACC-250-LD	3-50W	Socket - Wireless				1	
KlikAanKlikUit	AWMD-250	3-24W	Module - Wireless					
KlikAanKlikUit	ACM-250-LD	3-50W	Wireless				1	
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-3	1-3	1-5	1-3	1-3
Tradim	2485H	3-70W	R,C - Turn	1-3	1-3	1-5	1-3	1-3
Tradim	2490HP	5-70W	R,C - Turn		1-3	1-5	1-3	1-3
Tradim	63103X-1	1x27W	Floor	1-3	1-3	1-5	1-3	1-3
Yokis	MTV500E	5-250W	Module	1-3	1-3	1-5	1-3	1-3
Yokis	MTV500M	5-250W	DIN rail	1-3	1-3	1-5	1-3	1-3

* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels (≤ 20%)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior. *only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

Spiraled Basic



				A60 3W	G45 3W	G45 3W	C35 3W	T45 5W
Clear				143618	143313	143620	143315	
Gold				143619	143314	143621	143316	143624
Brand	Model	Load (LED)	Type	Dimming compatibility				
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1	1	1	1	1
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-5	1-5
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-5	1-5
Gira	238500	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-5	1-5
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1-5	1-5	1-5	1-5	1-5
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-5	1-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5
Klemko	891042	1-200W	R,C - Turn	1-5	1-5	1-5	1-5	1
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-5	1-5	1-5	1-5
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-5	1-5
Tradim	2490HP	5-70W	R,C - Turn	1-5	1-5	1-5	1-5	1-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5	1-5	1-5	1-5
Tradim	63103X-1	1x27W	Floor	1-5	1-5	1-5	1-5	1-5
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5

* Recommended dimmer

Spiraled Nostlagic



				A60 4W	ST64 4W	R63 4W
Clear				143030	143033	143036
Gold				143031	143034	143037
Black				143032	143035	143038
Brand	Model	Load (LED)	Type	Dimming compatibility		
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn			
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-5	1-5
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-5	1-5
Gira	238500	3-100W	R,L,C - Touch	1	1	1
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1-5	1-5	1-5
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1	1	1
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5
Klemko	891042	1-200W	R,C - Turn	1-5	1-5	1-5
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-5	1-5
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5
Tradim	2490HP	5-70W	R,C - Turn	1	1	1
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1	1	1
Tradim	63103X-1	1x27W	Floor	1-5	1-5	1-5
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5

* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels ($\leq 20\%$)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior. ¹ only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

Spiraled Original



	Thomas 4W	Marion 4W	Alva 4W	William 4W	Leslie 4W	Madeleine 4W
Clear	80100038462	80100038463	80100038654	80100040208	80100038655	80100039427
Gold	80100039071		80100039073	80100039967	80100039074	
Metal					80100039076	

Brand	Model	Load (LED)	Type	Dimming compatibility					
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7
Busch-Jaeger	6526U	2-100W	R,L,C - Touch	1-7	1-7	1-7	1-7	1-7	1-7
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-7	1-7	1-7	1-7	1-7	1-7
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-7	1-7	1-7	1-7	1-7	1-7
Gira	226200**	3-100W	R,L - Turn						
Gira	238500	3-100W	R,L,C - Touch	1-2	1-2	1-2	1-2	1-2	1-2
Gira	239000**	3-100W	R - Touch	1-7	1-7	1-7	1-7	1-7	1-7
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1-5	1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1-5'	1-5'	1-5'	1-5'	1-5'	1-5'
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-5	1-5	1-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5
Jung	225NVDE	3-100W	R,L - Turn	1-5'	1-5'	1-5'	1-5'	1-5'	1-5'
Klemko	890300	1-100W	C - Module	1-3	1-3	1-3	1-3	1-3	1-3
Klemko	891042	1-200W	R,C - Turn	1-3'	1-3'	1-3'	1-3'	1-3'	1-3'
KlikAanKlikUit	ACC-250-LD	3-50W	Socket - Wireless	1	1	1	1	1	1
KlikAanKlikUit	AWMD-250	3-24W	Module - Wireless						
KlikAanKlikUit	ACM-250-LD	3-50W	Wireless	1	1	1	1	1	1
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-7	1-7	1-7	1-7	1-7	1-7
Niko	310-02800	2-100W	R,C - Touch 3-wire	1-10	1-10	1-10	1-10	1-10	1-10
Niko	310-02900	3-200W	Touch	1-10	1-10	1-10	1-10	1-10	1-10
Niko	310-03900	3-200W	Turn	1-10	1-10	1-10	1-10	1-10	1-10
Niko	330-0070X	5-200W	DIN rail	1-10	1-10	1-10	1-10	1-10	1-10
Niko	550-0034X	2 x 5-200W	DIN module	1-10	1-10	1-10	1-10	1-10	1-10
Tradim	2485H	3-70W	R,C - Turn	1-2	1-2	1-2	1-2	1-2	1-2
Tradim	2490HP	5-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-7	1-7	1-7	1-7	1-7	1-7
Tradim	63103X-1	1x27W	Floor	1-7	1-7	1-7	1-7	1-7	1-7
Tradim	6421X	1-100W	Cord	1	1	1	1	1	1
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	1-5

* Recommended dimmer



	Estelle 2.7W	Mary 2.7W	Charles 6W	Theo 6W
Clear	80100038459	80100038998	80100039428	80100039429
Gold	80100038998	142889		

Brand	Model	Load (LED)	Type	Dimming compatibility			
Bailey *	WW15031	3-70W	R,C - Turn	1-20	1-20	1-7	1-7
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-2 3-5	1-2 3-5	1-5	1-5
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn	1-7	1-7	1-3	1-3
Busch-Jaeger	6526U	2-100W	R,L,C - Touch	1-7	1-7		
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-20	1-20	1-5	1-5
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-20	1-20	1-5	1-5
Gira	226200**	3-100W	R,L - Turn				
Gira	238500	3-100W	R,L,C - Touch	1-2	1-2	1-2	1-2
Gira	239000**	3-100W	R - Touch	1-7	1-7		
Gira	245500	3-200W	Uni. Led - Turn			1-5	1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1-5	1-5		
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1 1 2-5	1 1 2-5	1 2-5	1 2-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5
Jung	225NVDE	3-100W	R,L - Turn	1	1 2-5		
Klemko	891042	1-200W	R,C - Turn	1-3'	1-3'		
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-20	1-20	1-3	1-3
Tradim	2485H	3-70W	R,C - Turn	1-3	1-3	1-6	1-6
Tradim	2490HP	5-70W	R,C - Turn	1-10	1-10	1-6	1-6
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-10	1-10	1-6	1-6
Tradim	6220X	1x19W	Cord	1-5	1-5		
Tradim	63103X-1	1x27W	Floor	1-20	1-20	1	1
Tradim	6421X	1-100W	Cord	1	1		
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5

* Recommended dimmer

LED Filament



	A60 4W	A60 5W	A60 8W	G45 4W	C35 4W	Cosy 4W	R50 4W	R63/R80 4W
Clear		80100040297	80100040298	80100041653	80100041657	80100041658	142694	142695
Frosted			80100041650	80100041655	142579			142696
Gold	143048		143049	143052	143054	143055		
				143053				

Brand	Model	Load (LED)	Type	Dimming compatibility															
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7		
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3		
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	2	3-5	2-5	2	3-5	2	3-5	2	3-5	2	3-5	2	3-5	2	3-5	
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-5	1-7	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5		
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-5	1-7	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5		
Gira	226200**	3-100W	R,L - Turn																
Gira	238500	3-100W	R,L,C - Touch	1	2-5	1-5	1-5	1	2-5	1	2-5	1	2-5	1	2-5	1	2-5		
Gira	239000**	3-100W	R - Touch			1-7													
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5		
Honeywell Peha	00260623	6-60W	R,L - Turn	1	2-5		1	2-5	1	2-5	1	2-5	1	2-5	1	2-5	1	2-5	
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1	2-5	1-5	1	2-5	1	2-5	1	2-5	1	2-5	1	2-5	1	2-5	
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	
Jung	225NVDE	3-100W	R,L - Turn																
Klemko	891042	1-200W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-5	1-7	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	
Tradim	2485H	3-70W	R,C - Turn	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	
Tradim	2490HP	5-70W	R,C - Turn	1	2-5	1-2	1-5	1	2-5	1	2-5	1	2-5	1	2-5	1	2-5	1	2-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5	1-2	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	
Tradim	6220X	1x19W	Cord		1	1													
Tradim	63103X-1	1x27W	Floor	1-5	1-2	1-2	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	
Tradim	6421X	1-100W	Cord	1-3			1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3	
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	

* Recommended dimmer



	G95 4W	G95 8W	G125 4W	G125 8W	ST64 4W	ST64 8W
Clear	142584	142585	142589	80100041652		
Opal	142586	142587	142590	142591		
Gold		142588		142592	143050	143051

Brand	Model	Load (LED)	Type	Dimming compatibility					
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn		1-3		1-3	1-3	1-3
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	2	3-5	2	3-5	2	3-5
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-7	1-5	1-7
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-5	1-5	1-7	1-5	1-7
Gira	238500	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-5	1	2-5
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1-5	1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1-5		1-5		1	2-5
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-5	1	2-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5
Klemko	891042	1-200W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-7	1-5	1-7	1-5	1-7
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-3	1-3	1-3
Tradim	2490HP	5-70W	R,C - Turn	1-5	1-5	1-5	1-5	1	2-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5	1-5	1-5	1-5	1-5
Tradim	6220X	1x19W	Cord		1		1		1
Tradim	63103X-1	1x27W	Floor	1-2	1-2	1-2	1-2	1-5	1-2
Tradim	6421X	1-100W	Cord	1-3		1-3		1-3	
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	1-5









* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels (≤ 20%)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior. * only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

LED Filament









T18 2.5W	DeCone 3.5W	Pyramid			Diamond		T. Martello 8W
							
142194 142195	80100039970	80100035704 80100035705 80100035456			80100035706 80100035707		143855

Brand	Model	Load (LED)	Type	Dimming compatibility													
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1	2-5	1-5											
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-7	1-7				1-5	1-7	1-5					1-5
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-7	1-7				1-5	1-7	1-5					1-5
Gira	238500	3-100W	R,L,C - Touch	1-5	1-5					1-5		1	2-5				
Gira	239000**	3-100W	R - Touch							1-7	1-7	1-7	1-7	1-7			
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5					1-5		1-5	1-5	1-5	1-5		1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1	2-5	1	2-5			1-5		1-5	1-5	1-5	1-5		1-5
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1	2-5	1	2-5			1-5		1	2-5				1-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5					1-5		1-5	1-5	1-5			1-5
Jung	225NVDE	3-100W	R,L - Turn														
Klemko	891042	1-200W	R,C - Turn	1	2-5	1	2-5			1-5		1-5	1-5	1	2-5		1-5
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-5	1-7	1-3	1-3	1-5	1-7	1-3	1-5	1-7	1-5			1-5
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-3	1			1-3	1	1-3	1	1-5			1-5
Tradim	2490HP	5-70W	R,C - Turn	1-5	1-2	3-5				1-5	1-2		1-5	1	2-5		1-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)		1					1-2							1-5
Tradim	63103X-1	1x27W	Floor	1-5	1-7	2-3	1-3	1-2	2-3	1-3	1-2	1-3	1-3	1-5			1-7
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-3	1-3			1-3	1-3	1-3	1-3	1-5			1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-3	1-3			1-3	1-3	1-3	1-3	1-5			1-5

* Recommended dimmer



G9 1.5W	G9 2.7W	T20 4W	T25 4W	T30 5W	BaiLinear 5W
					
80100038381 80100038382	80100038383 80100038384	143312	143286	80100035451 80100035453	80100041599 80100041616 80100041617 80100041618

Brand	Model	Load (LED)	Type	Dimming compatibility													
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn		1-2	3-5	2-5	2-5									
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-7	1-7	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-7	1-7	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5
Gira	238500	3-100W	R,L,C - Touch	1-7	1-7	1	2-5	1	2-5								
Gira	239000**	3-100W	R - Touch										1-7				
Gira	245500	3-200W	Uni. Led - Turn		2-5	1-5	1-5	1-5	1-5	1	2-5						
Honeywell Peha	00260623	6-60W	R,L - Turn			1	2-5	1	2-5								
Jung	1224LEDUDE	3-100W	R,L,C - Touch			1	2-5	1	2-5				1-5'				
Jung	1730DD	3-60W	R,L,C - Turn		1-5	1-5	1-5	1-5	1-5				1-5'				
Jung	225NVDE	3-100W	R,L - Turn		1-5'												
Klemko	891042	1-200W	R,C - Turn		2-5	1-5	1-5	1-5	1-5	1-2	3-5		1-5				1-5
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire		1-5	1-5	1-5	1-5	1-5	1-3			1-5				1-5
Tradim	2485H	3-70W	R,C - Turn		1-6	1-6	1-5	1-5	1-5				1-5				1-5
Tradim	2490HP	5-70W	R,C - Turn			1	2-5	1	2-5				1-2				1-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)		1-6	1-5	1-5	1-5	1-5	1-2							1-5
Tradim	63103X-1	1x27W	Floor		1-5	1-5	1-5	1-5	1-5	1-2							1-5
Yokis	MTV500E	5-250W	Module		1-5	1-5	1-5	1-5	1-5	1-5			1-5				1-5
Yokis	MTV500M	5-250W	DIN rail		1-5	1-5	1-5	1-5	1-5	1-5			1-5				1-5

* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels (≤ 20%)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior. 'only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

LED Filament Mirror



A60 TM 4W	A60 TM 8W	G45 TM 4W	G95 TM 4W	G95 TM 4W
143610	143611	143612 143613	143626	143627

Brand	Model	Load (LED)	Type	Dimming compatibility				
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn	1-3	1-3	1-3	1-3	1-3
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	2 3-5		2 3-5	2 3-5	2 3-5
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-7	1-5	1-5	1-5
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-7	1-5	1-5	1-5
Gira	238500	3-100W	R,L,C - Touch	1 2-5	1-5	1 2-5	1 2-5	1 2-5
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1 2-5		1 2-5	1 2-5	1 2-5
Jung	1224LEUDE	3-100W	R,L,C - Touch	1 2-5	1-5	1 2-5	1 2-5	1 2-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5
Klemko	891042	1-200W	R,C - Turn	1-5	1-5	1-5	1-5	1-5
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-7	1-5	1-5	1-5
Tradim	2485H	3-70W	R,C - Turn	1-3	1-3	1-3	1-3	1-3
Tradim	2490HP	5-70W	R,C - Turn	1 2-5	1-5	1 2-5	1 2-5	1 2-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5	1-5	1-5	1-5
Tradim	63103X-1	1x27W	Floor	1-5	1-2	1-5	1-5	1-5
Tradim	6421X	1-100W	Cord	1-3		1-3	1-3	1-3
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5

* Recommended dimmer



A60 TM 6W	G45 TM 3W	G125 TM 5W
80100036763	80100039365	80100037279
		80100041296

Brand	Model	Load (LED)	Type	Dimming compatibility			
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn	1-3			1-3
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	2 3-5	2 3-5	2 3-5	1-2 3-5
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-7	1-7	1-5
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-7	1-7	1-5
Gira	238500	3-100W	R,L,C - Touch	1 2-5	1 2-5	1 2-5	1 2-5
Gira	239000**	3-100W	R - Touch	1-7	1-7	1-7	
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5
Honeywell Peha	00260623	6-60W	R,L - Turn	1 2-5	1 2-5	1 2-5	1-5
Jung	1224LEUDE	3-100W	R,L,C - Touch	1 2-5	2 3-5	2 3-5	1 2-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5
Jung	225NVDE	3-100W	R,L - Turn				
Klemko	891042	1-200W	R,C - Turn	1 2-5	1-5	1-5	1-3'
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-7	1-7	1-3
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-5
Tradim	2490HP	5-70W	R,C - Turn	1-5	1-5	1-5	1 2-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1			
Tradim	63103X-1	1x27W	Floor	1-5	1-3	1-3	1
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5

* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels (≤ 20%)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior. ¹ only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

LED Filament Dim-to-Warm | 3000-2200K




C35 4W	G45 4W	A60 8W	G125 8W	R80 8W	G45 TM 2.7W	A60 TM 4W	G125 TM 8W
							
80100040291	80100040292	80100039080	80100040293	80100040294	80100040403	80100040404	80100040405

Brand	Model	Load (LED)	Type	Dimming compatibility										
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7	1-7		
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5		
Eltako	FUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-5	1-7	1-7	1-7	1-5	1-5	1-7	1-7		
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-5	1-7	1-7	1-7	1-5	1-5	1-7	1-7		
Gira	238500	3-100W	R,L,C - Touch	1-2	3-5	1-2	3-5	1-2	1-2	1	2-5	1-2	3-5	
Gira	239000**	3-100W	R - Touch											
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1	2-5	1-5	1-5	
Honeywell Peha	00260623	6-60W	R,L - Turn	1-2	3-5	1-2	3-5	1-5	1-5	1-5	1-2	3-5	1-5	
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-2	3-5	1-2	3-5	1-5	1-5	1	2-5	1-2	3-5	
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1	2-5	1-5	1-5	
Jung	225NVDE	3-100W	R,L - Turn	1-2'	3-5	1-2'	3-5			1	2-5	1-2'	3-5	
Klemko	890300	1-100W	C - Module			1	1	1					1	
Klemko	891042	1-200W	R,C - Turn	1-2	3-5	1-2	3-5			1-5	1-2	3-5		
KlikAanKlikUit	ACC-250-LD	3-50W	Socket - Wireless	1	1						1			
KlikAanKlikUit	AWMD-250	3-24W	Module - Wireless											
KlikAanKlikUit	ACM-250-LD	3-50W	Wireless	1	1						1			
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-5	1-7	1-7	1-7	1-5	1-5	1-5	1-7		
Niko	310-02800	2-100W	R,C - Touch 3-wire			1-10	1-10	1-10					1-10	
Niko	310-02900	3-200W	Touch			1-10	1-10	1-10					1-10	
Niko	330-0070X	5-200W	DIN rail			1-10	1-10	1-10						
Niko	550-0034X	2 x 5-200W	DIN module			1-10	1-10	1-10						
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	
Tradim	2490HP	5-70W	R,C - Turn	1-2'	3-5	1-2'	3-5	1-5	1-5	1-5	1	2-5	1-2'	3-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1	1	1-2	1-2	1-2			1		1-2	
Tradim	63103X-1	1x27W	Floor	1-5	1-5	1-2	1-2	1-2		1-5	1-5	1-5	1-2	
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	1-5	

* Recommended dimmer

LED Filament Wave | Long



Wave A60 6W	Wave C35 3W	Wave G45 3W	Wave Globe 3W	Long ST64 5.8W	Long G95 5.8W	Long G125 8.3W
						
80100036361	80100036364 80100036365	80100036360	80100039078 80100036458 80100036459	80100036362 80100037174	80100036366	80100036367

Brand	Model	Load (LED)	Type	Dimming compatibility							
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-20	1-20	1-7	1-7	1-7	1-7	
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn								
Busch-Jaeger	6526U	2-100W	R,L,C - Touch	1-7	1-7	1-7	1-7	1-7	1-7	1-7	
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-5	1-20	1-20	1-5	1-5	1-5		
Eltako	FUD61NPN	400W	R,L,C - Pulse 3-wire	1-7	1-20	1-20	1-7	1-7	1-7	1-7	
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-7	1-20	1-20	1-7	1-7	1-7	1-7	
Gira	238500	3-100W	R,L,C - Touch	1-5	1-20	1-20	1-5	1-5	1-5	1-2	
Gira	239000**	3-100W	R - Touch	1-7						1-7	
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-20	1-20	1-5	1-5	1-5	1-5	
Honeywell Peha	00260623	6-60W	R,L - Turn	1	2-5	1-20	1-20	1-5	1-5		
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-7	1	2-20	1	2-20	1	2-7	
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-20	1-20	1-5	1-5	1-5	1-5	
Klemko	890300	1-100W	C - Module								
Klemko	891042	1-200W	R,C - Turn	1	2-5	1	2-20	1	2-5	1-5	
KlikAanKlikUit	ACC-250-LD	3-50W	Socket - Wireless								
KlikAanKlikUit	AWMD-250	3-24W	Module - Wireless								
KlikAanKlikUit	ACM-250-LD	3-50W	Wireless								
Max4Tech	420SL	0-200W	R,L,C - 3-wire	1-7	1-7	1-7	1-7	1-7	1-7	1-7	
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-10	1-20	1-20	1-10	1-5	1-5	1-4	
Niko	310-02800	2-100W	R,C - Touch 3-wire	1-10	1-10	1-10	1-10				
Niko	310-02900	3-200W	Touch	1-10							
Niko	330-0070X	5-200W	DIN rail	1-10	1-10	1-10	1-10				
Niko	550-0034X	2 x 5-200W	DIN module	1-10	1-10	1-10	1-10				
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1-5	
Tradim	2490HP	5-70W	R,C - Turn	1	2-5	1	2-20	1	2-5	1	2-5
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5	1-5	1-5	1	1	1	
Tradim	6220X	1x19W	Cord								
Tradim	63103X-1	1x27W	Floor	1-5	1-20	1-20	1-5	1-5	1-5	1-3	
Yokis	MTV500E	5-250W	Module	1-5	1-20	1-20	1-5	1-5	1-5	1-5	
Yokis	MTV500M	5-250W	DIN rail	1-5	1-20	1-20	1-5	1-5	1-5	1-5	

* Recommended dimmer

LED Filament Pine



Brand	Model	Load (LED)	Type	Dimming compatibility							
Bailey *	WW15031	3-70W	R,C - Turn	1-7		1-7		1-7		1-7	
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn	1-3							
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-2	3-5	1-2	3-5	2	3-5	1	2-5
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-3		1-3		1-3		1-3	
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-3		1-3		1-3		1-3	
Gira	226200**	3-100W	R,L - Turn	-							
Gira	238500	3-100W	R,L,C - Touch	1	2-5	1	2-5	1-5		1	2-5
Gira	245500	3-200W	Uni. Led - Turn	1-5		1-5		1-5		1-5	
Honeywell Peha	00260623	6-60W	R,L - Turn	1	2-5	1	2-5	1	2-5	1	2-5
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1	2-5	1	2-5	1	2-5	1	2-5
Jung	1730DD	3-60W	R,L,C - Turn	1-5		1-5		1-5		1-5	
Jung	225NVDE	3-100W	R,L - Turn	-							
Klemko	891042	1-200W	R,C - Turn	1	2-5	1	2-5	1	2-5	1	2-5
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5		1-5		1-3		1-5	
Tradim	2485H	3-70W	R,C - Turn	1-5		1-5		1-3		1-5	
Tradim	2490HP	5-70W	R,C - Turn	1	2-5	1	2-5	1-3		1	2-5
Tradim	63103X-1	1x27W	Floor	1-5		1-5		1-5		1-5	
Yokis	MTV500E	5-250W	Module	1-5		1-5		1-5		1-5	
Yokis	MTV500M	5-250W	DIN rail	1-5		1-5		1-5		1-5	

* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels (≤ 20%)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior. ¹ only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

BaiSpot LED GU10



PAR11 3W	PAR16 6.5W	PAR16 5W	PAR16 5W	PAR16 7W	PAR16 6W	PAR16 5.5W	ES63 6W
							
80100041300 80100041301	80100041661	80100040408	80100040596	80100041606	142638	143307 143308 143309 143310	143102

Brand	Model	Load (LED)	Type	Dimming compatibility								
Bailey *	WW15031	3-70W	R,C - Turn	1	2-5	1-7	1-7	1-7	1-7	1-7	1-7	1-7
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn	1-3	1-3	1-3	1-3					
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-3	1-5	1-5	
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-7	1-3	1-3	1-5	1-5	
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-7	1-3	1-3	1-5	1-5	
Gira	226200**	3-100W	R,L - Turn	1-3'								
Gira	238500	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-5	1-5	1	1-5	1-5	
Gira	245500	3-200W	Uni. Led - Turn	1	2-5	1-5	1-5	1-5	1-3	1-5	1-5	
Honeywell Peha	00260623	6-60W	R,L - Turn	1-5		1-5	1-5		1-3	1-5	1-5	
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-5	1-5	1	1-5	1-5	
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-3	1-5	1-5	
Jung	225NVDE	3-100W	R,L - Turn									
Klemko	891042	1-200W	R,C - Turn	1-3'	1-5	1	2-5	1-5	1-5	1-3	1-5	1-5
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-3	1-5	1-5	1-7	1-5	1-3	1-5	1-5	
Tradim	2485H	3-70W	R,C - Turn	1-5	1-5	1-5	1-5	1-5	1-3	1-5	1-5	
Tradim	2490HP	5-70W	R,C - Turn	1-3	1-3	1-2	3-5	1-10	1-5	1-3	1-5	
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5	1-5	1-10	1-5	1-5	1-5	1-5	
Tradim	63103X-1	1x27W	Floor	1-5	1	2-5	1-5	1-10	1-5	1-3	1-5	1-5
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	1-3	1-5	1-5	
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	1-3	1-5	1-5	

* Recommended dimmer

BaiSpot LED Reflector | PAR



R50 5W	R63 7W	R80 9W	PAR20 7W	PAR30 13W	PAR38 18W	AR70 7W
						
141861	80100040925	80100040568	80100039963 142750	80100039964 80100041353	80100039965 80100041354	80100038364

Brand	Model	Load (LED)	Type	Dimming compatibility						
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-7	1-7	1-5	1-3	1-7
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn		1-3	1-3	1-3			
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-5	1-5	1-5	1-5	1-5	1-5	1
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-5	1-3	1-3		1-3		
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-5	1-3	1-3		1-3		
Gira	226200**	3-100W	R,L - Turn							
Gira	238500	3-100W	R,L,C - Touch	1-5	1-5	1-5	1-3	1-5	1-5	1
Gira	245500	3-200W	Uni. Led - Turn	1-5	1-5	1-5		1-5	1-5	1
Honeywell Peha	00260623	6-60W	R,L - Turn		1-5	1-5				1
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-5	1-5	1-5		1-5 ¹	1-5	1
Jung	1730DD	3-60W	R,L,C - Turn	1-5	1-5	1-5		1-5	1-5	1
Jung	225NVDE	3-100W	R,L - Turn							1
Klemko	891042	1-200W	R,C - Turn	1-5	1	2-5		1-5	1-3	1
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-5	1-3	1-5			1-5	1
Tradim	2485H	3-70W	R,C - Turn	1	2-5	1-5	1-5	1-5	1-5	1
Tradim	2490HP	5-70W	R,C - Turn	1-5	1-5	1-5		1-5	1-5	1
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1	2-5	1-5	1-5	1-5	1-5	1
Tradim	63103X-1	1x27W	Floor	1-5	1	1-5	1	1-5	1-5	1
Yokis	MTV500E	5-250W	Module	1-5	1-5	1-5	1-5	1-5	1-5	
Yokis	MTV500M	5-250W	DIN rail	1-5	1-5	1-5	1-5	1-5	1-5	

* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels (≤ 20%)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior, *only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

BaiSpot LED Black



PAR16 6W	PAR20 6W	PAR30 15W	PAR38 18W	PAR38 18W	AR111 12W	AR111 15W	AR111 12.5W
							
142639	142640	142641	142642	80100037383	80100036876 142802 142803 80100036878 142804 142805	80100036872 142798 142799 80100036874 142800 142801	142643 142644

Brand	Model	Load (LED)	Type	Dimming compatibility								
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-7	1-4	1-3	1-3	1-5	1-4	1-5	
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-3	1-3	1-3	1-3	1-5	1-5	1-5	1-3	
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-3	1-5	1-7	1-7	1-3	
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-3	1-5	1-7	1-7	1-3	
Gira	238500	3-100W	R,L,C - Touch	1-3	1-3	1-3	1-3	1-5	1	2-5	1	2-3
Gira	245500	3-200W	Uni. Led - Turn	1-3	1-3	1-3	1-3	1-5	1-5	1-5	1-3	
Honeywell Peha	00260623	6-60W	R,L - Turn	1-3	1-3	1	2-3	1-3	1-5	1	2-5	1-3
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-3	1-3	1-3	1-3	1-5	1-5	1	2-5	1-3
Jung	1730DD	3-60W	R,L,C - Turn	1-3	1-3	1-3	1-3	1-5	1-5	1	2-5	1-3
Klemko	891042	1-200W	R,C - Turn	1-3	1-3	1-3	1-3	1-5	1-5	1-2	3-5	1-3
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-3	1-3	1-3	1-3	1-5	1-7	1-7	1-3	
Tradim	2485H	3-70W	R,C - Turn	1-3	1-3	1-3	1-3	1-5	1-5	1-5	1-3	
Tradim	2490HP	5-70W	R,C - Turn	1-3 ¹	1-3				1	2-5	1	2-3
Tradim	63103X-1	1x27W	Floor	1-3	1-3	1-3	1-3	1-5	1-5	1-5	1-3	
Yokis	MTV500E	5-250W	Module	1-3	1-3	1-3	1-3	1-5	1-5	1-5	1-3	
Yokis	MTV500M	5-250W	DIN rail	1-3	1-3	1-3	1-3	1-5	1-5	1-5	1-3	

* Recommended dimmer

BaiSpot LED Low voltage

LED low voltage lamps are tested with 141406 dimmable electronic transformer 0-105W ~ LED 0-40W

GU5.3 6W	G53 12.5W	G53 12W	G53 16W	AR70 7.5W
				
142637	142645 142646	80100040817	143311	143325

Marque	Model	Load (LED)	Type	Dimming compatibility				
Bailey *	WW15031	3-70W	R,C - Turn	1-3	1-3	1-3	1-3	1-3
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-3	1-3	1-3	1-3	1-3
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-3	1-3
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-3	1-3
Gira	238500	3-100W	R,L,C - Touch		1-3	1-3	1-3	
Gira	245500	3-200W	Uni. Led - Turn		1-3	1-3	1-3	
Honeywell Peha	00260623	6-60W	R,L - Turn		1-3	1-3	1-3	
Jung	1224LEDUDE	3-100W	R,L,C - Touch		1-3	1-3	1-3	
Jung	1730DD	3-60W	R,L,C - Turn		1-3	1-3	1-3	
Klemko	891042	1-200W	R,C - Turn	1-3	1-3	1-3	1-3	1-3
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-3	1-3			
Tradim	2485H	3-70W	R,C - Turn	1-3	1-3	1-3	1-3	1-3
Tradim	2490HP	5-70W	R,C - Turn	1-3	1-3	1-3	1-3	1-3
Tradim	2494	2 x 3-50W	R,C - Turn (duo)					1-3
Tradim	63103X-1	1x27W	Floor	1-3	1-3	1-3	1-3	1-3
Yokis	MTV500E	5-250W	Module	1-3	1-3	1-3	1-3	1-3
Yokis	MTV500M	5-250W	DIN rail	1-3	1-3	1-3	1-3	1-3



* Variateur recommandé

	Good compatibility (no flicker, no noise) and can reach low dim levels (≤ 20%)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior. ¹ only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

LED R7s



R7s 78 6W	R7s 118 12W	R7s 118 300°	R7s 78 5W	R7s 118 10W	R7s 189 15W	R7s 8.5W	R7s 13.5W
							
142580 142581	142582 142583	80100040695	80100040565	80100040566	80100038760 80100038761	80100033322 80100033323	80100033324 80100033325

Brand	Model	Load (LED)	Type	Dimming compatibility							
Bailey *	WW15031	3-70W	R,C - Turn	1-7	1-5		1-5			1-7	1-5
Busch-Jaeger	6523U**	2-100W	R,L,C - Turn			1	1	1'	1-7		
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-3	1-3	1-3			1-3		1-3
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-3	1-3					1-7	1-7
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-3	1-3					1-7	1-7
Gira	238500	3-100W	R,L,C - Touch	1-3	1-3	1-3	1-3	1-3	1-3		1-3
Gira	245500	3-200W	Uni. Led - Turn	1-3	1-3	1-3	1-3'	1-3	1-3	1-3	1-3
Honeywell Peha	00260623	6-60W	R,L - Turn	1-3	1-3	1-3	1-3	1-3	1-3		1-3
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-3	1-3	1-3	1-3	1-3	1-3		1-3
Jung	1730DD	3-60W	R,L,C - Turn	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3
Klemko	891042	1-200W	R,C - Turn	1-3	1-3					1-3	1-3
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1
Tradim	2485H	3-70W	R,C - Turn	1-3	1-3		1-3				1-3
Tradim	2490HP	5-70W	R,C - Turn	1-3	1-3					1-3	1-3
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5						
Tradim	63103X-1	1x27W	Floor	1-3	1-3	1-3	1-3	1-3	1-3	1-3	1-3
Yokis	MTV500E	5-250W	Module	1-3	1-3						
Yokis	MTV500M	5-250W	DIN rail	1-3	1-3						

* Recommended dimmer

LED Compact



T28 E27 10W	T28 E27 12W	G9 5W	Ba15d T18 5W	Ba15d T18 6.3W	Ba15d T28 10W
					
80100041666	143323	142593	142594	143859	143324

Brand	Model	Load (LED)	Type	Dimming compatibility					
Bailey *	WW15031	3-70W	R,C - Turn	1-6	1-5	1-7	1-7	1-7	1-6
Busch-Jaeger	6523U-102	2-100W	R,L,C - Turn	1-3	1-3				1-3
Eltako	EUD61NPN	400W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-3	1-3	1-3
Eltako	FUD61NPN	100W	R,L,C - Pulse 3-wire	1-3	1-3	1-3	1-3	1-3	1-3
Gira	238500	3-100W	R,L,C - Touch	1-3	1-3	1-3	1-3	1-3	1-3
Gira	245500	3-200W	Uni. Led - Turn	1-3	1-3	1-3	1-3	1-3	1-3
Honeywell Peha	00260623	6-60W	R,L - Turn	1-3	1-3			1-3	1-3
Jung	1224LEDUDE	3-100W	R,L,C - Touch	1-3	1-3	1-3	1-3	1-3	1-3
Jung	1730DD	3-60W	R,L,C - Turn	1-3	1-3	1-3	1-3	1-3	1-3
Klemko	891042	1-200W	R,C - Turn	1-3	1-3	1-3	1-3	1-3	1-3
Niko	310-0190X	5-200W	R,L,C - Turn 3-wire	1-3	1-3	1-3	1-3	1-3	1-3
Tradim	2485H	3-70W	R,C - Turn	1-3	1-3	1-3	1-3	1-3	1-3
Tradim	2490HP	5-70W	R,C - Turn	1-3	1-3	1-3	1-3	1-3	1-3
Tradim	2494	2 x 3-50W	R,C - Turn (duo)	1-5	1-5				1-5
Tradim	63103X-1	1x27W	Floor	1-3	1-3	1-3	1-3	1-3	1-3
Yokis	MTV500E	5-250W	Module	1-3	1-3	1-3	1-3	1-3	1-3
Yokis	MTV500M	5-250W	DIN rail	1-3	1-3	1-3	1-3	1-3	1-3

* Recommended dimmer

	Good compatibility (no flicker, no noise) and can reach low dim levels ($\leq 20\%$)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior, ' only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.

LED lamps and Dimmer Compatibility

General: A LED lamp is an electronic, low wattage device which makes it essentially different from incandescent or halogen lamps. Consequently the dimmable effects are not 100% comparable. Due to the enormous variety of dimmers in the market and difference in quality, it is impossible to give a general advice on which dimmer to use for LED lamps. 100% compatibility can never be guaranteed. Depending on the dimmer occurring effects may include noise, flickering and different peeks in light output.

Other external factors that may influence the dimming effects are:

- Other electrical appliances are connected on the same electrical circuit
- Variations in the mains voltage sine wave
- Total wattage exceeds the allowed dimmer (LED) load
- Total wattage is below minimum load of the dimmer
- Too many lamps on 1 dimmer
- Use of different item numbers on one dimmer is not recommended
- Electronic components can lead to acoustic noise in unfavourable conditions

Bailey has carefully tested a series of dimmers in combination with the Bailey dimmable Led lamps. the results you will find in our dimming list. The testing of dimmers is a continuous process and therefore the list is updated on a regular basis. The absence of a certain dimmer on the list does not mean it is incompatible, it only means we have not tested it yet. The tests are conducted in a testing environment and consequently the results in different fields of application may differ due to various factors. Bailey cannot be held responsible or liable for the results. In general best dimming results are obtained with trailing edge dimmer types (sometimes with neutral wire for installation). Please carefully follow the dimmer manufacturer's installation instructions and guidelines.

	Good compatibility (no flicker, no noise) and can reach low dim levels ($\leq 20\%$)
	Good compatibility in combination with dim stabilizer or compensator.
	Limited dimming range but stable behavior. [†] only in combination with dim stabilizer.
	Not compatible, possible flicker, noise and/or unstable behavior.
	Lamps not tested with dimmer.

General Notes	Possible light flickering may occur on low lightlevels. Dimming behaviour can be improved by using a dim stabilizer or compensator. Without this the lamp may have a limited dimming range or will be unstable.
**	Dimmer is discontinued (no longer available).
1-7	Minimum and maximum number of lamps this dimmer can control.